
Quick Reference Guide – Mitel 6920 IP Phone



Getting started

programmable keys.



headset. If you are using a DHSG/EHS headset, ensure

Warning! The headset port is for headset use only. Plugging any other devices into this port may cause damage to the phone and will void your warranty.

Activating your phone

Help is available

Follow the Installation Guide for the Mitel 6930 IP Phone to co After the phone boots, press the ACTIVATE soft key.	The certain priority to your network.
Enter your numeric OfficeSuite UC extension and then enter your r	numeric PIN.
Press ENTER or the # key and your phone will login and be ready for	or use.
To program speed dial and feature keys, login to the Hosted IP portal	at https://hostedipphonesystem.net/
Basic call handling	
Making a call 1. Lift the handset or press the key, and dial the number. 2. Press the Line programmable key and dial the number.	
Ending a call Place the handset back in its cradle, press the End Call softkey, or p	oress the key.
Answering a call Lift the handset or press the key for hands-free operation.	
Redialing Press the Redial softkey once or the key twice to call the la Home screen – or –	ast dialed number as displayed on the
Press the key once to access the Call History application wi the up and down navigation keys to scroll through the entries and a softkey to redial the selected number.	
Muting Press the key while on an active call to mute the micropho Press the key again to unmute the audio.	ne for your handset, headset, or speaker
Holding and resuming 1. To place an active call on hold, press the key. A (() (hold), 2. To resume the call, press the way again or press the resp	· · · · · · · · · · · · · · · · · · ·

For more information about your Hosted IP Phone System visit www.glaciernetworks.net

